

## Multitimer adjustable device

<h3>Wiring Diagram</h3>		<h3>Functioning Scheme</h3>	
		<h4>Delay ON</h4>	<h4>Delay OFF</h4>

This is an electronic device that operates after a single impulse in the same way as timer relay but the delay is not pre determined.

Choose between 10 time frames and chose the exact delay by the other trimmer.

Our Code	Rated Voltage	Amperage	TIME DELAY	OPTIONS TABLE			
				Delay OFF	Delay ON		
160927	12V	10A	Between 0,5 sec. to 6 hour	0	0,5 ... 10S	5	0,5 ... 6H
				1	5 ... 60S	6	5 ... 60M
				2	0,5 ... 10M	7	0,5 ... 10M
				3	5 ... 60M	8	5 ... 60S
160928	24V	10A	Between 0,5 sec. to 6 hour	4	0,5 ... 6H	9	0,5 ... 10S

Materials			
Baseplate	Nylon PA 6,6 + 30% Glass fibre Black	Terminals	Cu Zn (6,3X0,8 mm)
Cap	Nylon PA 6,6 + 15% Glass fibre Black		
Additional Data			
In conformity with:	ISO 7588 - DIN 46244 - ISO 8092	EU Dir. 2002/95/EC RoHS	DIN 4000: IP 5K4 Terminals pointing downwards
		DIR. 95/54 CE REG. 10 ECE-ONU/2	EMC DIN 40839